

A Novel Transparent UWB Antenna for Photovoltaic Solar Panel Integration and RF Energy Harvesting

T. Peter, *Student Member, IEEE*, T. A. Rahman, *Member, IEEE*, S. W. Cheung, *Senior Member, IEEE*, R. Nilavalan, *Senior Member, IEEE*, and H. F. AbuTarboush, *Member, IEEE*, A. Vilches, *Member, IEEE*

Abstract—A novel transparent UWB antenna for photovoltaic solar-panel integration and RF energy harvesting is proposed in this paper. Since the approval by the Federal Communications Committee (FCC) in 2002, much research has been undertaken on ultrawide band (UWB) technology especially for wireless communications. However, in the last decade, UWB has also been proposed as a power harvester. In this paper, a transparent cone top tapered slot antenna covering the frequency range from 2.2 GHz to 12.1 GHz is designed and fabricated to provide UWB communications whilst integrated onto to solar panels as well as harvest electromagnetic waves from free space and convert them into electrical energy. The antenna when sandwiched between an a-Si solar panel and glass is able to demonstrate a quasi Omni-directional pattern that is characteristic of a UWB. The antenna when connected to a 2.55-GHz rectifier is able to produce 18 mV DC in free space and 4.4 mV DC on glass for an input power of 10 dBm at a distance of 5 cm. Although the antenna presented in this paper is a UWB antenna, only an operating range of 2.49 to 2.58 GHz for power scavenging is possible due to the limitation of the narrowband rectifier used for the study.

Index Terms— energy, rectenna, transparent, uwb

I. INTRODUCTION

TRANSPARENT antennas for communications have been researched on by only a dedicated few for the last two decades [1-9]. These antennas were either semi-transparent like those with antenna geometries made of opaque conductive materials on a transparent substrate such as polymers or fully transparent such as those designed on transparent conductive oxides (TCOs) like ITO, AgHT or PEDOT [10-11]. The uniqueness of the latter type was the discreteness and the conformability they provided by virtue of the flexible nature of the substrate. In recent years, integration of solar cells with a transparent antenna was studied for harvesting energy from the sun [12]. However, this was on a narrowband antenna which becomes directional as a result of the opaque solar cells or panel which tend to act as a reflector. This thus limits the potential of such an antenna for window glass applications. Similarly, introducing an opaque material like an amorphous-silicon (a-Si) solar panel with an aluminum back electrode will also make a UWB antenna directional.

However, in this paper, this is overcome through the design and development of a novel UWB antenna that can provide omni-directionality even though integrated on an a-Si solar panel with a metal aluminum back electrode or ground. This enables the UWB antenna to transmit and receive signals wirelessly on both sides of the glass of buildings and windows of homes. This is the first time a transparent UWB antenna capable of maintaining omni-directional pattern on a solar panel is demonstrated.

The transparent UWB antenna, when connected to a rectifying circuit, serves also as a rectenna. A rectenna is a special type of antenna that is used to directly convert microwave energy into DC electricity. The idea was initially mooted by Nikola Tesla 100 years ago but experimentally researched, presented and patented by Brown [13-14]. It was Brown who first proposed the term rectenna as it consisted of an antenna combined with a rectifying circuit to convert radio or microwave power to DC power. Since then numerous applications such as providing DC power from space by receiving a microwave beam transmitted to earth by a geostationary solar-power satellite and converting it into DC power [15], wireless power transmissions in distributed wireless sensor networks [16], RFID tags [17], health monitoring [18], and most recently in Nokia mobile phones to provide standby power [19] have been demonstrated.

However, the applications in [16-19] harbor around small antennas that need to be small in size to keep the devices small and compact in line with the current trend towards small size, compact and cost effective devices. In this paper, although a small compact transparent UWB Cone Top Tapered Slot Antenna (CTSA) covering a frequency range from 2.2 to 12.1 GHz is presented as a transceiver, solar harvester and a rectenna, the application is not limited to small devices as the target destination is its use on glass windows/panels of buildings. The ample glass space provides a limitless area for large transparent wide band antenna designs or UWB array implementation to harvest radio waves across a wide range of frequencies and provide strong gain ‘last mile’ connection for the futuristic UWB-over-fiber (UOF) network [20]. Such antennas on the glass of buildings besides providing wireless communications and allowing harvesting of solar energy can also scavenge relatively large

amounts of power from signals coming from miles away. Incorporating the rectifier circuit as an integral part of the antenna as in [21] could make it even more cost effective and efficient. Using enhanced rectifier circuits which are currently under study [22] could facilitate the simultaneous reception of data and conversion to DC power.

A basic model of two antennas combined using a Wilkinson power combiner can be used to explain how simultaneous power transmission and data transfer can be achieved. A Wilkinson power combiner is a split-T combiner with a resistive element placed between the two input arms, which has all three ports matched and at the same time provides isolation between the two input ports. Inequalities between the antenna elements in the array, due either to tolerance effects or to phase differences in the received signals, will cause a voltage difference to occur across the resistor and thus make a current flow through it [23]. This current is dissipated by the resistor thus providing isolation between the antenna elements. By replacing the resistor with a rectifier circuit, the inequalities in the received signals may be used for power conversion while maintaining the isolation between the antenna elements [23]. The DC power output will be larger for larger inequalities between the antenna elements. The inequality between the signals at the combiner input ports can be achieved by differing the lengths of the transmission lines from the antennas to the combiner input ports [23]. Hence by moving the rectifier from the port at the bottom of the feed line and connecting it between the input arms, the feed line port is freed for data transmission. With the input of the rectifier connected to the combiner input arms, DC power can be tapped through a load at its output. However, with glass being amply available, the use of dedicated antenna arrays to provide for power scavenging and data transmission separately would not be a constraint.

In this paper, a UWB CTSA antenna is demonstrated as part of a UWB transceiver laminated on an a-Si solar panel, and as a rectenna both in free space and on glass to provide wireless communication and harvest solar and RF energy. The antenna integrated solar panel and rectenna designs are presented in Section II. The measurement set-up for each application is elaborated further in Section III. The measurement results and analysis are presented in Section IV with the conclusion on the findings in Section V.

II. ANTENNA DESIGN

A. Antenna Design

The geometry of the proposed transparent antenna is shown in Fig. 1(a). The antenna is designed as a coplanar-waveguide (CPW) fed cone top tapered slot antenna inscribed on a thin TCO polymer film, AgHT-4, with an overall size of $W \times L = 17 \times 33.5 \text{ mm}^2$. The feed gap g is 0.1 mm, and the feed line is designed to slowly taper and merge into the radiator. The antenna is first studied laminated on a 2 mm thick glass, and later sandwiched between the 2 mm thick glass and an a-Si solar panel. The antenna is designed and studied using computer simulation with the optimized dimension listed in

Table 1. The antenna size should normally be smaller when fabricated on glass with a higher dielectric constant which is 5.7 for the 2 mm thick glass. However, this is not the case here because the thickness of the glass increases the size of the antenna. Hence in the sandwich configuration, the overall thickness of the glass is twice as that in the substrate configuration, resulting in a much bigger volume due to the size of the antenna as well as the thickness of the glass. Also, it needs to be pointed out that the optimized dimensions of the antenna on glass are the same whether it is laminated in the substrate or superstrate configuration. This is because the substrate base of the AgHT-8 film, PET is very thin and as such has minimal effect on the radiation energy in the superstrate configuration. A thicker PET in the superstrate configuration on the other hand, would have made the antenna appear sandwiched between the PET and glass causing it to give a different result to that of a substrate configuration. The CTSA is fabricated as shown in Fig. 1(b) for measurement.

The AgHT-4, a layer of silver sandwiched between two layers of tin oxide and coated onto a polyethylene terephthalate (PET) base, has a surface resistivity of $4 \Omega\text{-square}$, a conductivity of 250,000 S/m and a thickness of 0.175 mm, making it suitable for use on window glass of homes and buildings. It has a visible light transmittance (VBLT) of 75%. This metallized polymer is commercially used as a sun-shielding film to cut down heat and conserve energy in homes and buildings.




Fig. 1 a) Geometry of CTSA and b) Prototype of CTSA.

TABLE 1
DIMENSIONS (MM) OF THE ANTENNA GEOMETRY IN FIG. 1

Parameters	L	W	L ₁	L ₂	W ₁	g
Free space	33.5	17.0	11.3	15.8	7.5	0.1
2mm Glass	35.1	17.5	10.6	15.8	7.82	0.23
Sandwich 2mm Glass/Solar	44.6	25.5	7.86	19.3	11.04	0.28

B. Antenna Design for Solar Integration

For solar harvesting applications, the CTSA is sandwiched between a 2 mm glass superstrate representing a glass window and an a-Si solar panel (model: QF 8368) of 38 x 86 mm² as shown in the simulated structural view in Fig. 2. The a-Si solar cell has several layers as shown in Fig. 3. However, in computer simulation, the p-type and n-type layers are not included due to the difficulty in accurately modeling them. The solar panel as per manufacturer is designed to work in low light and cloudy conditions.




Fig. 2 Structural view of CTSA sandwiched between glass superstrate and a-Si solar panel.

Glass Substrate	1.8 mm
Tin Oxide (Transparent Electrode)	70 nm
p-type layer	10 nm
Amorphous Silicon	600 nm
n-type layer	50 nm
Aluminium Electrode	1000 nm

Fig. 3 Structure of a-Si solar cell.

C. Rectenna Design

For rectifying the electromagnetic (EM) signals in the rectenna, a narrowband rectifier designed in [24] is used in our studies, since it was the only handy rectifier available in our lab at the time of this work. However, the authors would like to highlight at this point that the CTSA in actual fact can be used as a broadband rectenna in conjunction with a broadband rectifier, and that a narrowband rectifier was used only to demonstrate in principle the CTSA's RF harvesting capability. The Microwave Office (MWO) circuit schematic of the rectifier used for simulation is shown in Fig. 4, which is a double-diode (HSMS-2850) rectifier designed to work at a frequency of 2.55 GHz and fabricated on a FR-4 microstrip board with a thickness of 1.6 mm and a dielectric constant of 4.2. The package inductance and capacitance are also modeled in the circuit schematic to give better accuracy. The voltage-doubler configuration used in the design helps improve the voltage sensitivity [24]. In Fig. 4, the rectifier circuit receives the EM energy from the antenna and converts it to DC power. The prototype of the integrated antenna-rectifier module or rectenna is shown in Fig. 5. In practical applications, the rectifier could be attached to a window sill and connected to

the antenna using a transparent feed line to maintain transparency. Alternatively, a transparent rectifier circuit could be designed and integrated onto the antenna with only the diodes and capacitors being noticeable, but this is left to future works.




Fig. 4 Schematic for voltage doubler.




Fig. 5 Prototype of CTSA-rectifier module.

III. MEASUREMENT SET-UP

A. Solar Energy

A prototype of the CTSA sandwiched between a 2 mm glass superstrate and the a-Si solar panel is fabricated and measured for gain and radiation pattern using the Satimo StarLab system. Also voltage output of the solar panel is taken in free space, laminated with the antenna, and with the antenna sandwiched between the solar panel and the 2 mm thick glass. This was carried out to see whether AgHT-4's (VBLT) of 75% and the glass thickness affected the performance of the a-Si solar panel. The solar panel has a conversion rate of more than 15% and is able to deliver a voltage of 5.5 V and a current of 70 mA as per the manufacturer's specification in free space. An additional voltage output measurement for the solar panel with the prototype connected to a Vector Network Analyzer (VNA) is also taken to see whether EM transmission in anyway affects the performance of the solar panel. The measurements are done in the ambient light of fluorescence lighting as well as outdoor in the sun.

B. RF Energy

A diagrammatic representation of the experimental set-up used for measuring the amount of RF power converted to DC power by the rectenna in free space is shown in Fig. 6. In Fig.

6, a single tone RF signal is generated using a signal generator and fed to a horn antenna. The rectenna placed at a certain distance is used to collect the RF signal transmitted from the horn and convert it to DC power. The amount of DC converted is used to measure the performance of the rectenna.




Fig. 6 Measurement set-up for the CTSA rectenna (diagrammatic representation).

The return loss for a -30 dBm input from a RF signal source with the rectifier output terminated with a 50- Ω load is shown in Fig. 7. It can be seen that the rectifier has a maximum return loss of 25 dB at around 2.55 GHz which is the frequency at which the rectifier has the maximum voltage sensitivity and optimum performance. This is further verified by feeding a signal with frequency from 2.5 to 2.6 GHz at a step of 0.01 GHz to the rectifier input with the output terminated with a 50- Ω load resistor and recording the output voltage at each step. The results are listed in Table 2 which indicates a maximum output of 25.6 mV at 2.55 GHz. However, it should be noted from Fig. 7 that the rectifier, with a load of 50 Ω , has a 10 dB operating bandwidth from 2.49-2.58 GHz, thus when integrated with an antenna, the rectifier should be able to convert RF signals in this operating range to DC power. This is evident from [25], since although the loop antenna presented there has a narrow 10 dB operating bandwidth of 900-952 MHz, the rectifier is still able to receive and rectify electromagnetic waves in the neighbouring frequencies within the 10 dB operating bandwidth of the rectifier from 785 MHz to 1150 MHz.

With the CTSA connected to the rectifier output, the return loss of the rectenna is measured again with results also shown in Fig. 7 for comparison. It can be seen that the return loss is maximum at 2.53 GHz due to a mismatch. This is expected since an available rectifier in the lab was used for the study rather than one that was specifically designed to impedance match the antenna.

The horn antenna used in our studies shown in Fig. 6 has an average gain of 9.8 dB for the range 2.5 to 2.6 GHz. To determine the optimum operating frequency of the CTSA rectenna, the horn antenna is connected to a signal generator to serve as a transmit antenna. The CTSA rectenna is then placed at the receiver end 5 cm away to receive the signal as shown in Fig. 6. A 50- Ω load is connected to the rectenna output to tap the rectified DC. The output voltages at steps of 0.01 GHz for a signal frequency sweep from 2.5 to 2.6 GHz are shown in Table 3. It can be seen that the CTSA rectenna

has a maximum output of 9.4 mV at 2.53 GHz. This confirms the system has an optimum operating frequency of 2.53 GHz for a 50- Ω load. More measurements have been done with a 100- Ω load with results also shown in Table 3, indicating that the optimum operating frequency shifts to 2.51 GHz with a maximum output voltage of 18.0 mV, higher than the case with a 50- Ω load.




Fig. 7 Return losses of rectifier and rectenna.

TABLE 2
OUTPUT VOLTAGE OF RECTIFIER FOR -30 DBM INPUT POWER

Frequency (GHz)	2.50	2.51	2.52	2.53	2.54	2.55	2.56	2.57	2.58	2.59	2.60
Voltage (mV)	14.8	16.5	17.8	19.6	23.6	25.6	22.4	20.9	18.2	14.4	10.5

TABLE 3
OUTPUT VOLTAGE OF RECTENNA FOR -30 DBM INPUT POWER

	Frequency (GHz)	2.50	2.51	2.52	2.53	2.54	2.55	2.56	2.57	2.58	2.59	2.60
	50 Ω	Voltage (mV)	7.1	8.4	8.8	9.4	9.2	9.2	9.1	8.6	7.5	7.4
	Frequency (GHz)	2.50	2.51	2.52	2.53	2.54	2.55	2.56	2.57	2.58	2.59	2.60
	100 Ω	Voltage (mV)	17.8	18	17	16.7	15.3	16	16.4	17	16	15.4

IV. RESULTS AND ANALYSIS

A. Solar Energy

The simulated and measured return losses of the CTSA in free space, laminated on the a-Si solar panel and sandwiched between the solar panel and 2 mm glass superstrate are all shown in Fig. 8 for comparison. The discrepancy between the simulated and measured return losses in free space is mainly attributed to the accuracy of the parameters used to model the AgHT-4 material in simulation and fabrication accuracy of the prototype. Additional discrepancies between the simulated and measured return losses when the CTSA is laminated on the a-Si solar panel, and when sandwiched between the 2 mm glass, is attributed to the accuracy of the parameters used to model the a-Si solar panel and the uncertain air gaps between the CTSA, a-Si solar panel and 2 mm glass.




Fig. 8 Simulated and measured return loss of CTSA in free space, on solar panel only, and sandwiched between solar panel and glass.




Fig. 9 Overall simulated and measured gains of CTSA in free space, on solar panel only, and sandwiched between solar panel and glass.





Fig. 10 Measured radiation patterns for CTSA in free space, on solar panel and sandwiched between a-Si solar panel and 2 mm glass at 3, 5, 7 and 10 GHz.

The overall simulated and measured realized peak gains of the CTSA in free space, laminated on the a-Si solar panel and sandwiched between a-Si solar panel and the glass superstrate are shown in Fig. 9. The antenna has quite low gains due to the high resistance of the AgHT-4 materials. The measured gain on an average varies from 3 dB to 5 dB lesser than that of free space. When the antenna in free space and laminated on the a-Si solar panel, the simulated and measured gains agree well. When the antenna is sandwiched between the solar panel and glass superstrate, the simulated and measured results also agree well at frequencies below 5 GHz. However, a large discrepancy occurs at higher frequencies, probably due to the uncertain air gap on both sides.

The measured radiation patterns in the X-Y plane at different frequencies are depicted in Fig. 10. The measured radiation patterns for the sandwich configuration are seen to be quasi-omni directional for all the four different frequencies tested at 3, 5, 7 and 10 GHz. However, the results are quite encouraging as this allows wireless communication access inside and outside the building when the solar panel integrated antenna module is mounted onto a glass window or glass building. Additional endeavours of course are needed to further improve the gain to enhance transmission range and one way of doing this is through arrays.

Table 4 gives the voltage output obtained from the a-Si solar panel in the ambient light of the fluorescence lighting of a room and under the sun. A 5 K Ω load resistor was used so that the voltage output would be large enough for comparison in the different conditions.

TABLE 4
OUTPUT VOLTAGE OF CTSA SOLAR MODULE (MV)

	Ambient Light		Sun
	VNA (Off)	VNA (On)	
Solar only	102.9	–	4.5
CTSA + Solar	76.1	74.4	4.5
Glass+CTSA+Solar	68.6	68.7	4.7
Glass+Solar	93.2	–	4.5

A drop of 40% in voltage output is observed for the integrated module of the CTSA sandwiched between the glass and solar panel when compared to the voltage output of the solar panel only. Also, the energy harvesting performance of the module is not affected in any way when it was connected to the VNA to measure the return loss. The low output in the sun is because the solar panel is designed to operate in poor lighting conditions.

B. RF Energy

Rectenna in Free Space

The solar energy harvested may not be dependent on the antenna, but the RF energy is. The gain of the antenna at which the rectifier is designed needs to be high to aid the RF to DC conversion of the EM waves harvested.

The rectenna's efficiency, η_{rectenna} for free space and on glass is given by,

$$\eta_{\text{rectenna}} = \eta_{\text{rectifier}} \times \eta_{\text{antenna}} \quad \dots (1)$$

From Fig. 6, by knowing the transmitted power (P_T), gain of the transmitter (G_T) and measuring the distance (d) between the horn and the antenna under test (AUT) and the DC rectified power (P_{dc}) and calculating the received RF power (P_{ac}) by the antenna, we are able to determine the rectenna efficiency from (2) to (4) given below where A_{eff} is the effective antenna aperture,

$$P_{ac} = \frac{P_T \cdot G_T}{4\pi d^2} \times A_{\text{eff}} \quad \dots (2)$$

$$= \frac{P_T \cdot G_T}{4\pi d^2} \times \frac{G_R \times \lambda^2}{4\pi} \quad \dots (3)$$

$$P_{dc} = P_{ac} \times \eta_{\text{rectifier}} \quad \dots (4)$$

Therefore,

$$\text{rectifier efficiency, } \eta_{\text{rectifier}} = P_{dc} / P_{ac} \quad \dots (5)$$

Hence from (1),

$$\text{rectenna efficiency} = P_{dc} / P_{ac} \times \eta_{\text{antenna}}$$




Fig. 11 Measured output power of CTSA rectenna versus input power on 50- Ω and 100- Ω load at 2.51 and 2.53 GHz in free space.




Fig. 12 Measured rectenna system efficiencies at 2.51 and 2.53 GHz at 50- Ω and 100- Ω loads in free space.

A maximum rectifier efficiency of 49% is observed over a 100- Ω load for a 0 dBm input power at 2.51 GHz. The rectenna system efficiency is determined by taking the output power for varying power inputs from -30 dBm (0.001 mW) to 0 dBm (1mW). The measured output powers and efficiencies of the rectenna at the frequencies of 2.51 and 2.53 GHz and with 50- Ω and 100- Ω loads for different input power levels in free space are shown in Figs. 11 and 12. It can be seen in Fig. 11 that there is no output power if the input power is below about -15 dBm, which is due to the requirement of power to turn on the rectifying diodes. The output powers for 100- Ω load are higher than those for 50- Ω load, which agree with the results of Table 3. The measured system efficiency in Fig. 12 increases with load but at the different operating frequencies as earlier pointed out in Table 3. Although the efficiency in Fig. 12 is notably low, this could be improved via arrays and also larger antennas or redesigning the geometry to have better gain at the desired frequency of operation.

Rectenna on Glass

The same design of the CTSA on glass takes on a slightly larger or smaller size depending on the dielectric constant and thickness of the glass used. A higher dielectric constant could

further improve the gain. However, a higher thickness could possibly attenuate the received signal and consequently deteriorate the efficiency of the system. Nevertheless, the dimensions of the antenna design should be optimized to obtain the maximum gain possible at the frequency of operation.




Fig. 13 Simulated and measured return loss of rectenna on glass.




Fig. 14 Output voltage optimum at 2.57 GHz for 50-Ω and 100-Ω loads at 10-dBm input on 2 mm glass. Free space results given for comparison.




Fig. 15 Measured gain of CTSA on 2 mm glass substrate.

The optimized size of the CTSA for use on a 2 mm thick glass with a dielectric constant of 5.7 is given in Table 1. In our design, the CTSA on-glass is only 0.8 % bigger than that of free space. The simulated and measured return losses on glass are presented in Fig. 13. The difference between the simulated and measured return losses here are attributed to

fabrication accuracy and the uncertain air gap between the CTSA and 2 mm glass.

The voltage output for the CTSA on a 2 mm glass is shown in Fig 14. The voltage output is optimum at 2.57 GHz. The lower voltage output for the CTSA on glass is attributed to the lower gain at 2.57 GHz in comparison to that of the CTSA in free space as shown in Fig. 15. Hence at frequencies between 6-7 GHz and 8-9 GHz, higher voltage output can be expected.

Comparison with Existing Rectenna Solutions

A brief comparison with existing narrowband and broadband solutions so far published is presented to show that the CTSA rectenna is comparable as well as has several advantages. The most important consideration for a rectenna design is how to obtain high efficiency. This is usually done in two ways: i) to collect and deliver maximum power to the rectifying diode, and ii) to acquire high rectifier conversion efficiency through suppression of harmonics generated by the diode which re-radiate from the antenna as power lost. To maximize the delivered power, antennas arrays [26-29], broadband and UWB antennas [30-35], circularly polarized (CP) antennas [36-37], have been built to increase conversion efficiency. The antenna arrays increase incident power delivered to the rectifier diode by enlarging antenna aperture and increasing antenna gain, while the broadband and UWB antennas enable relatively high RF power to be collectively received from various sources in their frequency range. CP antennas meanwhile offer better power reception through less polarization mismatch. Harmonic suppression has been achieved by way of introducing, microwave components such as a low pass filter (LPF) between the antenna and diode as well as on the dc output side of the diode, and using optimized rectenna design that has harmonic rejection capabilities thus eliminating LPFs [38-39].

The rectifying circuit of the proposed CTSA rectenna has LPFs incorporated thus enabling it to suppress harmonics generated by the diodes. Although, RF harvesting between 2.49-2.58 GHz only is demonstrated here, the CTSA as a UWB antenna is capable of harvesting at various frequencies within its bandwidth range. The CTSA is smaller in size compared to those in [26-39], and has additional advantages as it can scavenge on both sides of the antenna due its omnidirectional characteristic and be aesthetically fitted on to glass panels of windows and buildings. Moreover, using a UWB antenna, the aperture is kept constant at higher frequencies compared to narrowband patch antennas which would shrink in size with increase in frequency.

The performance of the rectenna in terms of conversion efficiency is comparable to those previously reported [25], [36], and [38]. The conversion efficiency of 49% that was achieved for the rectifier in this study over a 100 Ω load could be higher if a larger load resistance is used. Conversion efficiency is dependent on the load resistor since, P_{dc} in equation (5) when expanded is,

$$P_{dc} = V_{dc}^2 / R_L \quad \dots (6)$$

$$= I_{dc}^2 \times R_L \quad \dots (7)$$

Where V_{dc} is the voltage observed at the load resistor, R_L and I_{dc} , the rectified dc current that flows into the load resistor. Hence from (7), higher the load resistor used, higher the rectified DC power and consequently, higher the rectifier efficiency.

The only limitations seen with the CTSA is the very short distance of 5 cm over which it could be used to harvest RF energy. It is comparatively low compared to the next highest distances achieved of 40 cm [40] and 57 cm [24] with slightly bigger narrowband antennas of $40 \times 40 \text{ mm}^2$ [41] and $30 \times 30 \text{ mm}^2$ [24] respectively at similar operating frequencies. This mainly stems from the low gain of the antenna which is a resultant of the low conductivity and high loss of the AgHT-4 material. This could be overcome in future by using a high gain and highly transparent nano technology TCO which is currently under development at the lab of our industrial collaborators [41].

Fidelity Factor

The Fidelity Factor (FF) measures the distortion produced by an antenna when radiating an input signal. The FF of the CTSA in free space, on the 2 mm glass, and sandwiched between the a-Si solar panel and 2 mm glass is shown in Fig. 16. Only simulated results are shown here as the VNA used in the studies had limited measurement options.




Fig. 16 Fidelity Factor of the CTSA: a) free space b) on 2 mm glass substrate c) sandwiched between solar panel and 2 mm glass.

The time domain response to calculate the FF was obtained by using the reference and received signal. A simulated 7.5 GHz bandwidth Gaussian signal centered at 6.85 GHz was applied as the reference signal at the input port and a virtual probe was placed at a distance of 300 mm from the antennas. The FF of the CTSA in free space = 0.8802, on 2 mm glass = 0.9273, and sandwiched between solar panel and 2 mm glass = 0.9601. The FFs obtained indicate good correlation between the normalized input and transmitted signals in simulation.

V. CONCLUSION

A novel transparent UWB CTSA that can maintain its omnidirectionality when integrated onto solar panels as well as harvest RF energy besides being able also to provide wireless communication has been presented. This makes the CTSA excellent for on-glass applications as it can provide a 3-in-1 solution in providing sun shielding from harmful UV rays, wireless communication and energy harvesting. The capability of the antenna in delivering a quasi omni-directional pattern even though sandwiched between an opaque a-Si solar panel and glass makes it able to provide wireless transmission and reception on both sides of a glass window or glass building. Finally, the work presented in this paper lends weight and credibility to the fact that transparent antennas like those made from AgHT or even other TCOs when utilized on glass windows, could potentially also become the new “last mile” connection for next generation wireless communications via UOF.

ACKNOWLEDGEMENT

This work was funded by the Universiti Teknologi Malaysia (UTM) under the Post-Doctoral Fellowship Scheme for the project: “Development of PV Solar Harvest System”.

REFERENCES

- [1] R. N. Simons and R. Q. Lee, “Feasibility Study of Optically Transparent Microstrip Patch Antenna” International Symposium and Radio Science Meeting cosponsored by IEEE, AP-S, and U.R.S.I., Montreal, Canada, July 13-18, 1997.
- [2] C. Mias, C. Tsakonas, N. Prountzos, D.C. Koutsogeorgis, S. C. Liew, C. Oswald, R. Ranson, W. M. Cranton, C. B. Thomas, “Optically transparent microstrip antennas,” Antennas for Automotives (Ref. No. 2000/002), IEE Colloquium on , vol., no., pp.8/1-8/6, 2000.
- [3] J. A. Nessel, A. Zaman, R.Q. Lee, K. Lambert, “Demonstration of an X-Band Multilayer Yagi- Like Microstrip Patch Antenna With High Directivity and Large Bandwidth” Antennas and Propagation Society Symposium, IEEE, vol. 1B, 227 – 230, 2005.

- [4] N. Guan, H. Furuya, D. Delaune, K. Ito, "Antennas Made of Transparent Conductive Films", PIERS proceedings, China, p. 720, March, 2008.
- [5] A. Katsounaros, Y. Hao, N. Collings, W. A. Crossland, "Optically transparent antenna for Ultra Wide-Band applications," Antennas and Propagation, 2009. EuCAP 2009. 3rd European Conference on , vol., no., pp.1918-1921, 23-27 March 2009.
- [6] N. J. Kirsch, N. A. Vacirca, E. E. Plowman, T. P. Kurzweg, A. K. Fontecchio, K. R. Dandekar, "Optically transparent conductive polymer RFID meandering dipole antenna," RFID, 2009 IEEE International Conference on , vol., no., pp.278-282, 27-28 April 2009. N. Kawasaki, "Parametric study of thermal and chemical nonequilibrium nozzle flow," M.S. thesis, Dept. Electron. Eng., Osaka Univ., Osaka, Japan, 1993.
- [7] T. Peter and R. Nilavalan, "Study on the performance deterioration of flexible UWB antennas," Antennas and Propagation Conference Loughborough (LAPC'09), pp. 669-672, 2009.
- [8] T. Peter, R. Nilavalan, H. F. AbuTarboush, and S. W. Cheung, "A Novel Technique and Soldering Method to Improve Performance of Transparent Polymer Antennas," IEEE Antennas and Wireless Propagation Letters, vol.9, no., pp.918-921, 2010.
- [9] T. Peter, T. I. Yuk, R. Nilavalan, S. W. Cheung, "A Novel Technique to Improve Gain in Transparent UWB Antennas", Antennas and Propagation Conference Loughborough (LAPC'11), Nov. 2011.
- [10] T. Yasin, R. Baktur, C. Furse, "A comparative study on two types of transparent patch antennas," General Assembly and Scientific Symposium, 2011 XXXth URSI, vol., no., pp.1-4, 13-20 Aug. 2011.
- [11] Transparent Flexible Conductive Polymer Antennas – Drexel University.
- [12] S. V. Shynu, M. J. R. Ons, P. McEvoy, M. J. Ammann, S. J. McCormack, B. Norton, "Integration of Microstrip Patch Antenna With Polycrystalline Silicon Solar Cell," Antennas and Propagation, IEEE Transactions on , vol.57, no.12, pp.3969-3972, Dec. 2009 "Antenna Technologies Advance for MIMO Era", Nikkei Electronics Asia, p. 4, September, 2008.
- [13] W. C. Brown, "The History of Power Transmission by Radio Waves," Microwave Theory and Techniques, IEEE Transactions on , vol.32, no.9, pp. 1230- 1242, Sep 1984.
- [14] W. C. Brown, U.S. Patent 3 434 678, Mar. 25, 1969.
- [15] W. C. Brown, "Status of the Microwave Power Transmission Components for the Solar Power Satellite," IEEE Trans. Microwave Theory Tech, vol. MTT-29, no.12, pp 1319-1327, Dec. 1981.
- [16] K. M. Z. Shams, M. Ali, "Wireless power transmission to a buried sensor in concrete", IEEE Sensor J 7, (2007), 1573-1577.
- [17] B. Strassner, K. Chang, "Passive 5.8 GHz Radio Frequency Identification Tag for Monitoring Oil Drill Pipe", IEEE Trans. Microwave Theory Tech, vol. 51, no. 2, pp. 356-363, Feb. 2003.
- [18] V. Sakamuri, J. Frolik, "Design of a 2.4 GHz interrogator for a rectenna-based sensor system," Wireless and Microwave Technology Conference (WAMICON), 2011 IEEE 12th Annual , vol., no., pp.1-4, 18-19 April 2011.
- [19] D. G. Rowe, "Nokia developing phone that recharges itself without mains electricity", www.guardian.co.uk, Wed. 10 June 2009.
- [20] Xu Xing, Zhou Enbo, Liang Yu, T. I. Yuk, K. S. Lui, K. K. Y. Wong, "Power-efficient photonic BPSK coded ultrawideband signal generation," Optical Fiber Communication Conference and Exposition (OFC/NFOEC), 2011 and the National Fiber Optic Engineers Conference , vol., no., pp.1-3, 6-10 March 2011.
- [21] T.-U. Hong, K.-M. Oh, H.-W. Lee, H. Nam, T.-S. Yun, D.-S. Lee, H.-I. Hwang and J.-C. Lee, "Novel broadband rectenna using printed monopole antenna and harmonic-suppressed stub filter," Microwave and Optical Technology Letters, 52: 1194-1197, 2010.
- [22] H. J. Visser, R. J. M. Vullers, "Design Equations for Small Loop-Based Rectennas", Antennas and Propagation Conference Loughborough (LAPC'11), Nov. 2011.
- [23] H. J. Visser, Approximate Antenna Analysis for CAD, John Wiley & Sons, Chichester, UK, 2009.
- [24] K. W. Lui, A. Vilches, C. Toumazou, "Ultra-efficient microwave harvesting system for battery-less micropower microcontroller platform," Microwaves, Antennas & Propagation, IET , vol.5, no.7, pp.811-817, May 13 2011.
- [25] R. H. Chen, Y. C. Lee, and J. S. Sun, "Design and Experiment of a Loop Rectenna for RFID Wireless Power Transmission and Data Communication Applications," PIERS Proceedings, 528-531, Beijing, China, Mar. 23-27, 2009.
- [26] N. Shinohara and H. Matsumoto, "Experimental study of large rectenna array for microwave energy transmission," IEEE Trans. Microwave Theory Tech., vol. 46, pp. 261-268, Mar. 1998.
- [27] Y. J. Ren and K. Chang, "5.8-GHz Circularly Polarized Dual-Diode Rectenna and Rectenna Array for Microwave Power Transmission," IEEE Trans. Microwave Theory Tech., vol. 54, no. 4, pp. 1495-1502, 2006.
- [28] S. Dasgupta, B. Gupta and H. Saha, "Development of Circular Microstrip Patch Antenna Array for Rectenna Application", IEEE INDICON 2010, Kolkata, INDIA December 17-19, 2010.
- [29] W. Huang, B. Zhang, X. Chen, K.-M. Huang, and C.-J. Liu, "Study on an s-band rectenna array for wireless microwave power transmission," Progress In Electromagnetics Research, Vol. 135, 747-758, 2013.
- [30] J. A. Hagerty and Z. Popovic, "An experimental and theoretical characterization of a broadband arbitrarily-polarized rectenna array," in Proc. IEEE MTT-S Int. Microwave Symp. Dig., vol. 3, Phoenix, AZ, June 2001, pp. 1855-1858.
- [31] A. Slavova and A. S. Omar, "Wideband rectenna for energy recycling," in Proc. IEEE AP-S Int. Symp. Dig. , Columbus, OH, June 2003, pp. 954-957.
- [32] D. Bouchouicha, F. Dupont, M. Latrach L. Ventura, "Ambient RF energy harvesting", In International Conference on Renewable Energies and Power Quality, Granada, Spain, 2010.
- [33] J. A. Hagerty, N. D. Lopez, B. Popovic and Z. Popovic, "Broadband Rectenna Arrays for Randomly Polarized Incident Waves," 30th European Microwave Conference, vol., no., pp. 1-4, Oct. 2000.
- [34] D. Bouchouicha, F. Dupont, M. Latrach, L. Ventura, "Ambient RF Energy Harvesting," International Conference on Renewable Energies and Power Quality, Spain, pp. 1-5, March 2010.
- [35] C. M. Ghiglini, "Ultra-Wideband (UWB) rectenna design for Electromagnetic Energy Harvesting," Ph.D. dissertation, Department of Theory of Signal Communications, Telecommunications Technology Centre of Catalonia, Pontifical Catholic University of Peru, 2010.
- [36] J. Heikkinen and M. Kivikoski, "A Novel Dual-Frequency Circularly Polarized Rectenna," IEEE Antennas and Wireless Propagation Letters, vol. 2, pp. 330-333, 2003.
- [37] B. Strassner and K. Chang, "5.8-GHz circularly polarized dualrhombic-loop traveling-wave rectifying antenna for low power-density wireless power transmission applications," IEEE Trans. Microwave Theory Tech., vol. 51, pp. 1548-1553, May 2003.
- [38] A. Georgiadis, G. Andia and A. Collado, "Rectenna Design and Optimization Using Reciprocity Theory and Harmonic Balance Analysis for Electromagnetic (EM) Energy harvesting," IEEE Antennas and Wireless Propagation Letters, vol. 9, pp. 444-446, 2010.
- [39] J. Y. Park, S. M. Han, and T. Itoh, "A rectenna design with harmonic-rejecting circular-sector antenna," IEEE Antennas Wireless Propag. Lett., vol. 5, no. 1, pp. 52-54, 2004.
- [40] M. Ali, G. Yang, and R. Dougal, "Miniature circularly polarized rectenna with reduced out of band harmonics," IEEE Antennas and Wireless Propagat. Lett., vol. 5, no. 1, pp. 107-110, 2006.
- [41] Self-Aligning Nano Particles for Transparent Electronics. Available at: <http://www.cimananotech.com>.



Thomas Peter (IEEE SM'09, M'13) received the B. Eng and M.Eng in Electrical Engineering from University Teknologi Malaysia in 2001 and 2007 respectively. He received the PhD degree from the Department of Electronics and Computer Engineering in the area of Antennas and Propagation from Brunel University, London, UK in 2012. His PhD work was

mainly on Optically Transparent Antennas for UWB and Energy Harvesting. He was attached as a Research Associate at the Dept of Electrical Engineering, Hong Kong University from Jan-Mar, 2011. He is currently working as a Post-Doctoral Research Fellow in the area of Transparent Antenna Arrays for LTE Applications at the Wireless Communication Centre, Faculty of Electrical Engineering, Universiti Teknologi Malaysia (UTM). He has published over 11 technical papers in international journals and conferences. He also served as a reviewer for a number of international conferences and an international journal. Prior to pursuing his PhD and joining UTM, Dr Thomas worked as a Senior Engineer at Stats ChipPAC Ltd (Singapore), a semi-conductor plant involved in providing high-end packaging solutions for ICs on Chips from 1999 to 2008.



Tharek Abd Rahman received the BSc (Hons) in Electrical Engineering from University of Strathclyde, UK in 1977, MSc in Communication Engineering from UMIST, Manchester, UK in 19982 and PhD in Mobile Communications from the University of Bristol, UK in 1988. From 1992 to 1995 he served as an Assoc Professor and from 1997 till now as Professor of wireless communication at the Universiti Teknologi Malaysia (UTM).

He has played an important leading role in mobile communication standardization in Malaysia and has worked closely with government agencies and industries in research and consultancies such as Nippon Telegraph and Telephone Japan (NTT), Ministry of Defense Malaysia, Standard and Industrial Research Institute of Malaysia (SIRIM), Malaysian Commission and Multimedia Malaysia (MCMC), Petronas, Maxis, Celcom, Ericson, Motorola, Nokia, ATSB and Angkasa. Dr Tharek holds various positions which include Head of Radio Communication Engineering Department, Head of Focus Group and Deputy Dean (Research and Post Graduate) in the Faculty of Electrical Engineering, UTM. He is also the Director of Wireless Communication Centre (WCC), Faculty of Electrical Engineering from 2003 till now. His current research areas are related to 4G for mobile communications, satellite communications, antennas and propagation.

Dr Tharek has published more than 200 scientific papers in journals and conferences and obtained many national and international awards with gold medals such as in PECIPTA and MTE (Malaysia), INPEX (USA), BIS (UK), SIFF (Korea). He has also successfully managed to commercialize the product, "Wireless Bridge for Point to Point Access" which is currently being used in UTM, MTDC (UTM, UPM and UKM technovation parks) and SIRIM Berhad in Malaysia. Up to now 13 PhD students have graduated under his supervision in the area of wireless communication.



S W Cheung received the BSc degree with First Class Honours in Electrical and Electronic Engineering from Middlesex University, U.K. in 1982 and the PhD degree from Loughborough University of Technology, U.K. in 1986. From 1982 to 1986, he was a research assistant in the Department of Electronic and Electrical Engineering at Loughborough University of Technology, where he collaborated with Rutherford Appleton

Laboratory and many UK universities to work on a project for new generations of satellite systems.

Dr Cheung is an Associate Professor at the University of Hong Kong and in charge of the Microwave, RF Frequency and Telecom Laboratories. His current research interests include antenna designs, 2G, 3G and 4G mobile communications systems, MIMO systems and satellite communications systems. He is a senior member of the IEEE and has been serving the IEEE in Hong Kong for the past twenty years. In 2009 and 2010, he was the Chairman of the IEEE Hong Kong Joint Chapter on Circuits and Systems and Communications. He was the Honorary Treasurer and currently the Chair-Elect of the IEEE Hong Kong Section.



R. Nilavalan (IEEE M'05, SM'10) received the B.Sc. Eng. in Electrical and Electronics Engineering from University of Peradeniya, Sri Lanka in 1995 and PhD in Radio Frequency Systems from University of Bristol, Bristol, UK in 2001. From

1999 to 2005 he was a researcher at the Centre for Communications Research (CCR) at University of Bristol, UK. At Bristol, his research involved theoretical and practical analyses of post reception synthetic focusing concepts for near-field imaging and research on numerical FDTD techniques. Since 2005, he has been with the Electronics and Computer Engineering subject area, Brunel University, UK, where he is currently a senior lecturer in wireless communications. His main research interests include antennas and propagation, microwave circuit designs, numerical electromagnetic modelling and wireless communication systems. He has published over 100 papers and articles in journals and international conferences in his research area. Dr Nilavalan was a member of the European commission, Network of Excellence on Antennas (2002 - 2005) and a member of the IET.



Hattan F. Abutarboush (M'07) received the B.Sc Honours degree in Electrical Communications and Electronics Engineering from Greenwich University, London, UK, in 2005 and the MSc degree in Mobile Personal and Satellite Communications from the Department of Electrical and Electronics Engineering, Westminster University, London, UK, in 2007. He received the PhD degree from the Department of Electronics and Computer Engineering, in Antennas and

Propagation from Brunel University, London, UK, in July 2011. His PhD research work was mainly on Fixed and Reconfigurable Multiband Antennas. He was a research visitor to Hong Kong University and National Physical Laboratory (NPL), Teddington, UK in 2010. He was a research fellow at King Abdullah University of Science and Technology (KAUST) working on mm-wave antennas and inkjet printed antennas from 2011 to 2013. He also worked as a research associate for the American University in Cairo (AUC) from April to July 2011 where he worked on the packaging of novel MEMS antennas. Currently, he is working as a research assistant in microwave medical imaging at Bristol University, Bristol, UK.

Dr. Abutarboush received the Vice-Chancellor's Prize Award for the Best Doctoral Research for 2011 from Brunel University, London, UK and the outstanding achievement Award from the Saudi Arabian Cultural Bureau in London, for the outstanding overall achievement in the PhD degree. He has authored/co-authored over 40 technical papers in international journals and conferences. He also has served as reviewer for different international journals and conferences in the areas of antennas and propagation. His current research interests lie in the design of reconfigurable antennas, antennas for mobile phones, RF/microwave circuit design, mm-wave antennas, on-chip antennas, lens antennas and microwave medical imaging for breast and brain cancer detection.

Antonio Vilches BEng (Hons) DIC PhD is a Lecturer in the School of Engineering and Design at Brunel University, Uxbridge, teaching programming, electronics and embedded systems at undergraduate level. His areas of interest include microwave antenna design, low-power devices, analogue circuit design and embedded solutions for biomedical applications. He was previously employed as a Research Fellow at the Institute of Biomedical Engineering at Imperial College London, UK. He has been consulted by international electronics manufacturers including Daimler-Chrysler (Germany) and Sharp UK. He has authored/co-authored 20+ peer-reviewed journal publications and filed 2 patents.

